

3K Electric Battery Specifications (LM)

EB Battery Specification (LM)

| Model | Terminal Type | Voltage | Capacity | Battery Dimension (mm.) | | | |
|----------|---------------|---------|------------|-------------------------|-----|-----|-----|
| | | | Ah/ 20 Hrs | L | W | H | TH |
| EB25LL | L | 12 | 30 | 195 | 127 | 200 | 227 |
| EB25T | T | 12 | 30 | 195 | 127 | 200 | 222 |
| EB35LL | L | 12 | 42 | 236 | 127 | 200 | 227 |
| EB35T | T | 12 | 42 | 236 | 127 | 200 | 222 |
| EB50LL | L | 12 | 60 | 256 | 170 | 201 | 228 |
| EB50LR | L | 12 | 60 | 256 | 170 | 201 | 228 |
| EB50T | T | 12 | 60 | 256 | 170 | 201 | 224 |
| EB50V | V | 12 | 60 | 256 | 170 | 201 | 250 |
| EB65LL | L | 12 | 80 | 303 | 170 | 201 | 228 |
| EB65LR | L | 12 | 80 | 303 | 170 | 201 | 228 |
| EB65T | T | 12 | 80 | 303 | 170 | 201 | 224 |
| EB65V | V | 12 | 80 | 303 | 170 | 201 | 250 |
| EB90T | T | 12 | 110 | 406 | 173 | 209 | 232 |
| EB100LL | L | 12 | 120 | 406 | 173 | 209 | 241 |
| EB100LR | L | 12 | 120 | 406 | 173 | 209 | 241 |
| EB100T | T | 12 | 120 | 406 | 173 | 209 | 232 |
| EB100V | V | 12 | 120 | 406 | 173 | 209 | 256 |
| EB130LL | L | 12 | 160 | 502 | 180 | 210 | 255 |
| EB130LR | L | 12 | 160 | 502 | 180 | 210 | 255 |
| EB130T | T | 12 | 160 | 502 | 180 | 210 | 255 |
| EB160LL | L | 12 | 190 | 505 | 220 | 210 | 255 |
| EB160LR | L | 12 | 190 | 505 | 220 | 210 | 255 |
| EB160T | T | 12 | 190 | 505 | 220 | 210 | 255 |
| EBB100V | V | 12 | 100 | 406 | 170 | 213 | 262 |
| EBB125LL | L | 12 | 125 | 406 | 170 | 213 | 245 |
| EBB125V | V | 12 | 125 | 406 | 170 | 213 | 262 |
| EBZ60T | T | 12 | 60 | 256 | 170 | 201 | 224 |
| EBZ80T | T | 12 | 80 | 303 | 170 | 201 | 224 |
| EBZ110T | T | 12 | 110 | 406 | 173 | 209 | 232 |
| EBZ130V | V | 12 | 125 | 406 | 170 | 213 | 262 |
| EBZ160T | T | 12 | 160 | 502 | 180 | 210 | 255 |
| EBZ200T | T | 12 | 200 | 505 | 220 | 210 | 255 |